

SERVICE BULLETIN

RS 356
August 2004

MODEL	SUBJECT
EX13, EX17, EX21, EX27	Change of Governor Spring

- **PURPOSE:**
To improve function
- **AFFECTED PRODUCTS:**
All EX series models
- **DETAILS OF CHANGE;**
Refer to page 2
- **PART NUMBERS AND INTERCHANGEABILITY:**
Refer to page 2
- **EXECUTION:**
EX13, 17 and EX21 for 60Hz (STD) : Already applied from end of September, 2003 production.
EX27 for 60Hz (STD) : Already applied from December 2003 production
EX13, 17, 21 and EX27 for 50Hz : Already applied from December 2003 production
Starting serial numbers:
EX13 ; 2115413 (and after)
EX17 ; 2124261 (and after)
EX21 ; 2104441 (and after)
EX27 ; 2110828 (and after)

- DETAIL OF THE CHANGE:**

Specifications of the governor spring has been changed.

After the Change

	EX13	EX17	EX21	EX27
60Hz (STD)	277-42510-03 Number of spring coils : 16 turns Color : Silver			279-42502-53 Number of spring coils " 19 turns Color : Silver + Blue paint
50Hz	279-42505-33 Number of spring coils : 25 turns Color : Yellow			



Before the Change

	EX13	EX17	EX21	EX27
60Hz (STD)	279-42502-43 Number of spring coils : 20 turns Color : Silver			
50Hz	276-42505-43 Number of spring coils : 16 turns Color : Yellow		279-42505-23 Number of spring coils : 18 turns Color : Yellow	

- PART NUMBER and INTERCHANGEABILITY:**

No.	Description	After Change		Interchangeability (Individual)	Before Change		Remarks
		Part Number	Qty		Part Number	Qty	
1	Governor Spring	277-42510-03	1	New Old	279-42502-43	1	EX13/17/21 (60Hz, STD)
2	Governor Spring	279-42502-53	1	New Old	279-42502-43	1	EX27 (60Hz, STD)
3	Governor Spring	279-42505-33	1	New Old	276-42505-43	1	EX13/17 (50Hz)
4	Governor Spring	279-42505-33	1	New Old	279-42505-23	1	EX21/27 (50Hz)